

Digital Design

COE 211

Sheet - 07

1. Identify each of the following expressions as **SOP**, **standard SOP**, **POS**, or **standard POS**:

a) $AB + \bar{A}BD + \bar{A}\bar{C}\bar{D}$

c) $(A + \bar{B} + C)(A + B + \bar{C})$

b) $\bar{A}BC + AB\bar{C}$

d) $(A + \bar{C})(A + B)$

2. Convert each SOP expression in Question 1 to standard form

3. Convert each POS expression in Question 1 to standard form

4. Convert the following SOP expression to an equivalent POS expression:

$$\bar{A}\bar{B}\bar{C} + \bar{A}B\bar{C} + \bar{A}BC + A\bar{B}C + ABC$$

